


# AT&T MOBILITY ANTENNA AMENDMENT PLAN




# **AMERICAN TOWER®**

ATC SITE NAME: MORLEY 1 ATC SITE NUMBER: 383495 AT&T MOBILITY SITE ID: COL06029 AT&T MOBILITY FA LOCATION CODE: 10093580 AT&T MOBILITY SITE NAME: MOUNT PITTSBURG SITE ADDRESS: 15743 PHANTOM CANYON VIEW COLORADO SPRINGS, CO 80903

AT&T MOBILITY IWM JOB NUMBER SITE OVERLAY.LTE.2ND CARRIER: WSUTH0032394 5G NR 1SR CBAND: WSUTH0032547 5G NR 1DR-2 SOFTWARE CARRIER: WSUTH0032475 5G NR 1DR-2 SOFTWARE CARRIER: WSUTH0032434 5G NR RRH SWAP: WSUTH0032589 LTE 1C RRH SWAP: WSUTH0032710



		5G NR 1SR CB	AND: WSUTH0032719					
COMPLIANCE CODE	PROJECT S	UMMARY	PROJECT DESCRIPTION		SHEET INDEX			
ALL WORK SHALL BE PERFORMED AND MATERIALS INSTALLED IN ACCORDANCE WITH THE CURRENT EDITIONS OF THE	SITE ADD		THE PROPOSED PROJECT INCLUDES MODIFYING GROUND BASED AND TOWER MOUNTED EQUIPMENT AS INDICATED PER BELOW:	SHEET NO:	DESCRIPTION:	REV:	DATE:	BY:
FOLLOWING CODES AS ADOPTED BY THE LOCAL GOVERNMENT AUTHORITIES. NOTHING IN THESE PLANS IS	15743 PHANTOM (		TOWER WORK: REMOVE (4) ANTENNA(S), (4) RRH(s), AND (2) TMA(s).	G-001	TITLE SHEET	0	11/20/24	CAM
TO BE CONSTRUED TO PERMIT WORK NOT CONFORMING TO THESE CODES.			INSTALL (6) ANTENNA(S), (6) RRU(s), (1) SQUID(S), (1) CABLE	G-002	GENERAL NOTES	0	11/20/24	CAM
1. 2021 INTERNATIONAL BUILDING CODE (IBC)	COUNTY: E		HOISTING ANCHOR(S), (3) CABLE HOISTING GRIP(S), (3) BACK TO	C-001	OVERALL SITE PLAN	0	11/20/24	CAM
2. 2020 NATIONAL ELECTRIC CODE (NEC)	<u>GEOGRAPHIC CC</u> LATITUDE: 3		BACK RRU BRACKET(S), (6) PIPE MOUNT(S), (12) CROSSOVER PLATE KIT(S), (1) 0.39" (10 mm) FIBER TRUNK(S), AND (2) 0.96" (24.3 mm) 6	C-101	DETAILED SITE PLAN	0	11/20/24	CAM
3. LOCAL BUILDING CODE 4. CITY/COUNTY ORDINANCES	LONGITUDE:		AWG 6 DC POWER TRUNK(S).	C-102		0	11/20/24	CAM
4. CITY/COUNTY ORDINANCES	GROUND ELEVATIO		EXISTING (1) SQUID(S), (4) 7/8" COAX CABLE(S), (4) 1-5/8" COAX					
	ZONING INFO	RMATION:	CABLE(S), (1) 0.39" (10 mm) FIBER TRUNK(S), AND (2) 0.78" (19.7 mm) 8 AWG 6 DC POWER TRUNK(S) TO REMAIN.	C-201	TOWER ELEVATION	0	11/20/24	CAM
	JURISDICTION: EL		GROUND WORK:	C-401	ANTENNA INSTALLATION	0	11/20/24	CAM
	PARCEL ID: 7		REMOVE (1) -48VDC/+24VDC POWER PLANT(S), (1) BATTERY	C-402	ANTENNA SCHEDULE	0	11/20/24	CAM
PROJECT NOTES			CABINET(S), (5) RECTIFIER(S), (2) CONVERTER(S), (20) GNB MARATHON M12V155FT BATTER(IES), (1) DC12(s), AND (2) NOKIA	C-501	CONSTRUCTION DETAILS	0	11/20/24	CAM
<ol> <li>THE FACILITY IS UNMANNED.</li> <li>A TECHNICIAN WILL VISIT THE SITE APPROXIMATELY ONCE</li> </ol>	PROJECT	ΓΤΕΑΜ	FSM4 BBU(s).	E-101	ELECTRICAL PANELS	0	11/20/24	CAM
A MONTH FOR ROUTINE INSPECTION AND MAINTENANCE. 3. THE PROJECT WILL NOT RESULT IN ANY SIGNIFICANT LAND	TOWER OWNER:	APPLICANT:	INSTALL (1) VERTIV NETSURE 5100 -48VDC/+24VDC POWER PLANT(S), (1) PURCELL FLX42 CABINET(S), (8) -48VDC RECTIFIER(S),	E-102	ONE-LINE DIAGRAM	0	11/20/24	CAM
DISTURBANCE OR EFFECT OF STORM WATER DRAINAGE. 4. NO SANITARY SEWER, POTABLE WATER OR TRASH	AMERICAN TOWER	AT&T MOBILITY	(1) VERTIV CONVERTER SHELF(VES), (6) -48VDC/-58VDC	E-103	GROUNDING PLAN	0	11/20/24	CAM
DISPOSAL IS REQUIRED. 5. HANDICAP ACCESS IS NOT REQUIRED.	10 PRESIDENTIAL WAY WOBURN, MA 01801		CONVERTER(S), (2) -48VDC/+24VDC CONVERTER(S), (12) ENERSYS POWERSAFE SBS-190F BATTER(IES), (1) DC12-48-60-0-25E(s),	E-501	GROUNDING DETAILS	0	11/20/24	CAM
<ol> <li>THE PROJECT DEPICTED IN THESE PLANS QUALIFIES AS AN ELIGIBLE FACILITIES REQUEST ENTITLED TO</li> </ol>	ENGINEER:	PROPERTY OWNER:	(3) 50A AIR6419 B77G DC BREAKER(S), (3) 50A AIR6419 B77D DC BREAKER(S), (3) 50A 4890 B25/B66 DC BREAKER(S), (3) 25A 4478 B14	R-601 - R-615	SUPPLEMENTAL			
EXPEDITED REVIEW UNDER 47 U.S.C. § 1455(A) AS A MODIFICATION OF AN EXISTING WIRELESS TOWER THAT	TEP	Z INVESTMENTS LLC	DC BREAKER(S), (1) 100A FLX FEED BREAKER(S), (2) 250A +24V CONV FEED DC BREAKER(S), (2) 15A 6651 BBU DC BREAKER(S), (1) 25A 6601					
INVOLVES THE COLLOCATION, REMOVAL, AND/OR REPLACEMENT OF TRANSMISSION EQUIPMENT THAT IS	326 TRYON RD	PO BOX 50005	DC BREAKER(S), (1) 6651 BBU(S), AND (1) 6601 SITE CONTROLLER(S).					
NOT A SUBSTANTIAL CHANGE UNDER CFR § 1.61000 (B)(7).	RALEIGH, NC 27603	COLORADO SPRINGS, CO 80949-0005						
	PROJECT LOCATIO	ON DIRECTIONS	1					
	OBEY ALL SPEED LIMITS AT ALL		UTILITY COMPANIES					
	DRIVEWAYS AND BLIND CURVI RIGHT ONTO TURKEY CANON RA MILES TURN LEFT ONTO HENRY COME TO GATE. PUNCH IN COMB	ES ALONG THE ROAD TURN NCH ROAD FROM HWY 115 1.3 RIDE HTS 1.3 MILES YOU WILL	POWER COMPANY: BLACK HILLSCORPORATION PHONE: (888) 890-5554					
Know what's <b>below.</b> <b>Call</b> before you dig.	TURN RIGHT ONTO PHANTON TOWERS AT	A CANYON VW .5 MILES TO	TELEPHONE COMPANY: CENTURYLINK PHONE: (866) 642-0400					



#### GENERAL CONSTRUCTION NOTES:

- OWNER FURNISHED MATERIALS, AT&T MOBILITY "THE COMPANY" WILL PROVIDE AND THE CONTRACTOR WILL INSTALL
  - A. BTS EQUIPMENT FRAME (PLATFORM) AND ICEBRIDGE SHELTER (GROUND BUILD/CO-LOCATE ONLY)
  - AC/TELCO INTERFACE BOX (PPC)
  - ICE BRIDGE (CABLE TRAY WITH COVER) (GROUND BUILD/CO-LOCATE ONLY, GC TO FURNISH AND INSTALL FOR ROOFTOP INSTALLATION)
  - D. TOWERS, MONOPOLES
  - TOWER LIGHTING
  - GENERATORS & LIQUID PROPANE TANK
  - G. ANTENNA STANDARD BRACKETS, FRAMES AND PIPES FOR MOUNTING ANTENNAS (INSTALLED BY OTHERS)
  - TRANSMISSION LINE
  - TRANSMISSION LINE JUMPERS
  - TRANSMISSION LINE CONNECTORS WITH WEATHERPROOFING KITS
  - TRANSMISSION LINE GROUND KITS
  - HANGERS
  - HOISTING GRIPS
- O. BTS EQUIPMENT
- 2 THE CONTRACTOR IS RESPONSIBLE TO PROVIDE ALL OTHER MATERIALS FOR THE COMPLETE INSTALLATION OF THE SITE INCLUDING, BUT NOT LIMITED TO, SUCH MATERIALS AS FENCING, STRUCTURAL STEEL SUPPORTING SUB-FRAME FOR PLATFORM, ROOFING LABOR AND MATERIALS, GROUNDING RINGS, GROUNDING WIRES COPPER-CLAD OR XIT CHEMICAL GROUND ROD(S), BUSS BARS, TRANSFORMERS AND DISCONNECT SWITCHES WHERE APPLICABLE, TEMPORARY ELECTRICAL POWER, CONDUIT, LANDSCAPING COMPOUND STONE, CRANES, CORE DRILLING, SLEEPERS AND RUBBER MATTING, REBAR, CONCRETE CAISSONS, PADS AND/OR AUGER MOUNTS, MISCELLANEOUS FASTENERS, CABLE TRAYS, NON-STANDARD ANTENNA FRAMES AND ALL OTHER MATERIAL AND LABOR REQUIRED TO COMPLETE THE JOB ACCORDING TO THE DRAWINGS AND SPECIFICATIONS. IT IS THE POSITION OF AT&T MOBILITY TO APPLY FOR PERMITTING AND CONTRACTOR RESPONSIBLE FOR PICKUP AND PAYMENT OF REQUIRED PERMITS
- ALL WORK SHALL CONFORM TO ALL CURRENT APPLICABLE FEDERAL, STATE, AND LOCAL CODES, INCLUDING ANSI/EIA/TIA-222, AND COMPLY WITH ATC CONSTRUCTION SPECIFICATIONS
- CONTRACTOR SHALL CONTACT LOCAL 811 FOR IDENTIFICATION OF UNDERGROUND UTILITIES PRIOR TO START OF CONSTRUCTION
- CONTRACTOR SHALL BE RESPONSIBLE FOR COORDINATING ALL REQUIRED INSPECTIONS
- ALL DIMENSIONS TO, OF, AND ON EXISTING BUILDINGS, DRAINAGE STRUCTURES, AND SITE IMPROVEMENTS SHALL BE VERIFIED IN FIELD BY CONTRACTOR WITH ALL DISCREPANCIES REPORTED TO THE ENGINEER.
- DO NOT CHANGE SIZE OR SPACING OF STRUCTURAL ELEMENTS 7
- DETAILS SHOWN ARE TYPICAL; SIMILAR DETAILS APPLY TO SIMILAR CONDITIONS UNLESS 8
- THESE DRAWINGS DO NOT INCLUDE NECESSARY COMPONENTS FOR CONSTRUCTION 9. SAFETY WHICH SHALL BE THE SOLE RESPONSIBILITY OF THE CONTRACTOR
- CONTRACTOR SHALL BRACE STRUCTURES UNTIL ALL STRUCTURAL ELEMENTS NEEDED 10. FOR STABILITY ARE INSTALLED. THESE ELEMENTS ARE AS FOLLOWS: LATERAL BRACING, ANCHOR BOLTS, ETC.
- CONTRACTOR SHALL DETERMINE EXACT LOCATION OF EXISTING UTILITIES, GROUNDS 11. DRAINS, DRAIN PIPES, VENTS, ETC, BEFORE COMMENCING WORK
- INCORRECTLY FABRICATED, DAMAGED, OR OTHERWISE MISFITTING OR NONCONFORMING MATERIALS OR CONDITIONS SHALL BE REPORTED TO THE AT&T MOBILITY REP PRIOR TO REMEDIAL OR CORRECTIVE ACTION. ANY SUCH REMEDIAL 12. ACTION SHALL REQUIRE WRITTEN APPROVAL BY THE AT&T MOBILITY REP PRIOR TO PROCEEDING
- EACH CONTRACTOR SHALL COOPERATE WITH THE AT&T MOBILITY REP, AND 13. COORDINATE HIS WORK WITH THE WORK OF OTHERS
- 14. CONTRACTOR SHALL REPAIR ANY DAMAGE CAUSED BY CONSTRUCTION OF THIS ROJECT TO MATCH EXISTING PRE-CONSTRUCTION CONDITIONS TO THE SATISFACTION OF THE AT&T MOBILITY CONSTRUCTION MANAGER.
- 15 ALL CABLE/CONDULT ENTRY/EXIT PORTS SHALL BE WEATHERPROOFED DURING INSTALLATION USING A SILICONE SEALANT
- WHERE EXISTING CONDITIONS DO NOT MATCH THOSE SHOWN IN THIS PLAN SET, 16. CONTRACTOR SHALL NOTIFY THE AT&T MOBILITY REP AND ENGINEER OF RECORD IMMEDIATELY
- CONTRACTOR SHALL ENSURE ALL SUBCONTRACTORS ARE PROVIDED WITH A COMPLETE AND CURRENT SET OF DRAWINGS AND SPECIFICATIONS FOR THIS PROJECT. 17.
- CONTRACTOR SHALL REMOVE ALL RUBBISH AND DEBRIS FROM THE SITE AT THE END OF 18. FACH DAY
- CONTRACTOR SHALL COORDINATE WORK SCHEDULE WITH AMERICAN TOWER CORPORATION (ATC) AND TAKE PRECAUTIONS TO MINIMIZE IMPACT AND DISRUPTION OF OTHER OCCUPANTS OF THE FACILITY.
- CONTRACTOR SHALL FURNISH AT&T MOBILITY AND AMERICAN TOWER CORPORATION 20. (ATC) WITH A PDF MARKED UP AS-BUILT SET OF DRAWINGS UPON COMPLETION OF WORK
- PRIOR TO SUBMISSION OF BID, CONTRACTOR SHALL COORDINATE WITH AT&T MOBILITY 21. REP TO DETERMINE WHAT, IF ANY, ITEMS WILL BE PROVIDED. ALL ITEMS NOT PROVIDED SHALL BE PROVIDED AND INSTALLED BY THE CONTRACTOR. CONTRACTOR WILL INSTALL ALL ITEMS

PROVIDED

PRIOR TO SUBMISSION OF BID. CONTRACTOR SHALL COORDINATE WITH AT&T MOBILITY 22 REP TO DETERMINE IF ANY PERMITS WILL BE OBTAINED BY CONTRACTOR. ALL REQUIRE PERMITS NOT OBTAINED BY AT&T MOBILITY MUST BE OBTAINED, AND PAID FOR, BY THE CONTRACTO

23. CONTRACTOR SHALL INSTALL ALL SITE SIGNAGE IN ACCORDANCE WITH AT&T MOBILITY SPECIFICATIONS AND REQUIREMENTS.

CONTRACTOR SHALL SUBMIT ALL SHOP DRAWINGS TO AT&T MOBILITY FOR REVIEW AND APPROVAL PRIOR TO FABRICATION.

25 ALL FOUIPMENT SHALL BE INSTALLED ACCORDING TO MANUFACTURER'S SPECIFICATIONS AND LOCATED ACCORDING TO AT&T MOBILITY SPECIFICATIONS, AND AS SHOWN IN THESE PLANS.

26. THE CONTRACTOR SHALL SUPERVISE AND DIRECT THE PROJECT DESCRIBED HEREIN THE CONTRACTOR SHALL BE SOLELY RESPONSIBLE FOR ALL THE CONSTRUCTION MEANS, METHODS, TECHNIQUES, SEQUENCES AND PROCEDURES AND FOR COORDINATING ALL PORTIONS OF THE WORK UNDER THE CONTRACT

CONTRACTOR SHALL NOTIFY AT&T MOBILITY, REP A MINIMUM OF 48 HOURS IN ADVANCE OF POURING CONCRETE OR BACKFILLING ANY UNDERGROUND UTLITIES, FOUNDATIONS OR SEALING ANY WALL, FLOOR OR ROOF PENETRATIONS FOR ENGINEERING REVIEW AND 

28. WHEN THE PROJECT SCOPE REQUIRES THE USE OF THE SAFETY CLIMB, THE GENERAL CONTRACTOR SHALL ENSURE THE SAFETY CLIMB IS FREE OF OBSTRUCTIONS, NOT RUBBING ON OR TRAPPED BY ANY INSTALLED CUSTOMER EQUIPMENT. IS VISUALLY TAUT. MEETS MANUFACTURER INSTALLATION SPECIFICATIONS, AND IS FIRMLY SECURED AT ALL CABLE GUIDE LOCATIONS UPON PROJECT COMPLETION.

29. COMPLETION OF PROJECT SHALL NOT OBSTRUCT, TRAP, LOOSEN, OR OTHERWISE CAUSE FAILURE TO MEET MANUFACTURER INSTALLATION REQUIREMENTS FOR THE SAFETY CLIMB.

CONTRACTOR SHALL BE RESPONSIBLE FOR SITE SAFETY INCLUDING COMPLIANCE WITH ALL APPLICABLE OSHA STANDARDS AND RECOMMENDATIONS AND SHALL PROVIDE ALL NECESSARY SAFETY DEVICES INCLUDING PPE AND PPM AND CONSTRUCTION DEVICES SUCH AS WELDING AND FIRE PREVENTION, TEMPORARY SHORING, SCAFFOLDING, TRENCH BOXES/SLOPING, BARRIERS, ETC

31. THE CONTRACTOR SHALL PROTECT AT HIS OWN EXPENSE, ALL EXISTING FACILITIES AND SUCH OF HIS NEW WORK LIABLE TO INJURY DURING THE CONSTRUCTION PERIOD. ANY DAMAGE CAUSED BY NEGLECT ON THE PART OF THIS CONTRACTOR OR HIS REPRESENTATIVES, OR BY THE ELEMENTS DUE TO NEGLECT ON THE PART OF THIS CONTRACTOR OR HIS REPRESENTATIVES, EITHER TO THE EXISTING WORK, OR TO HIS WORK OR THE WORK OF ANY OTHER CONTRACTOR. SHALL BE REPAIRED AT HIS EXPENSE TO THE OWNER'S SATISFACTION

ALL WORK SHALL BE INSTALLED IN A FIRST CLASS, NEAT AND WORKMANLIKE MANNER BY MECHANICS SKILLED IN THE TRADE INVOLVED. THE QUALITY OF WORKMANSHIP SHALL BE SUBJECT TO THE APPROVAL OF THE AT&T MOBILITY REP. ANY WORK FOUND BY THE AT&T REP TO BE OF INFERIOR QUALITY AND/OR WORKMANSHIP SHALL BE REPLACED MOBILITY AND/OR REWORKED AT CONTRACTOR EXPENSE UNTIL APPROVAL IS OBTAINED

IN ORDER TO ESTABLISH STANDARDS OF QUALITY AND PERFORMANCE, ALL TYPES OF MATERIALS LISTED HEREINAFTER BY MANUFACTURER'S NAMES AND/OR MANUFACTURER'S CATALOG NUMBER SHALL BE PROVIDED BY THESE MANUFACTURERS AS SPECIFIED.

AT&T MOBILITY FURNISHED EQUIPMENT SHALL BE PICKED-UP AT THE AT&T MOBILITY WAREHOUSE, NO LATER THAN 48HR AFTER BEING NOTIFIED INSURED, STORED, UNCRATE, PROTECTED AND INSTALLED BY THE CONTRACTOR WITH ALL APPURTENANCES REQUIRED TO PLACE THE EQUIPMENT IN OPERATION, READY FOR USE, THE CONTRACTOR SHALL BE RESPONSIBLE FOR THE EQUIPMENT AFTER PICKING IT UP

35. AT&T MOBILITY OR HIS ARCHITECT/ENGINEER RESERVES THE RIGHT TO REJECT ANY EQUIPMENT OR MATERIALS WHICH, IN HIS OWN OPINION ARE NOT IN COMPLIANCE WITH THE CONTRACT DOCUMENTS, EITHER BEFORE OR AFTER INSTALLATION AND THE EQUIPMENT SHALL BE REPLACED WITH EQUIPMENT CONFORMING TO THE REQUIREMENTS OF THE CONTRACT DOCUMENTS BY THE CONTRACTOR AT NO COST TO AT&T MOBILITY OR THEIR ARCHITECT/ENGINEER

#### SPECIAL CONSTRUCTION ANTENNA INSTALLATION NOTES:

1 WORK INCLUDED:

В.

C.

D

A. ANTENNA AND COAXIAL CABLES ARE FURNISHED BY AT&T MOBILITY UNDER A SEPARATE CONTRACT. THE CONTRACTOR SHALL ASSIST ANTENNA INSTALLATION CONTRACTOR IN TERMS OF COORDINATION AND SITE ACCESS. ERECTION SUBCONTRACTOR SHALL BE RESPONSIBLE FOR THE PROTECTION OF PERSONNEL

- INSTALL ANTENNAS AS INDICATED ON DRAWINGS AND AT&T MOBILITY SPECIFICATIONS.
- INSTALL GALVANIZED STEEL ANTENNA MOUNTS AS INDICATED ON DRAWINGS.
- INSTALL FURNISHED GALVANIZED STEEL OR ALUMINUM WAVEGUIDE.

E CONTRACTOR SHALL PROVIDE FOUR (4) SETS OF SWEEP TESTS USING ANRITZU-PACKARD 8713B RF SCALAR NETWORK ANALYZER. SUBMIT FREQUENCY DOMAIN REFLECTOMETER(FDR) TESTS RESULTS TO THE PROJECT MANAGER, SWEEP TESTS SHALL BE AS PER ATTACHED RFS "MINIMUM FIELD TESTING RECOMMENDED FOR ANTENNA AND HELIAX COAXIAL CABLE SYSTEMS" DATED 10/5/93. TESTING SHALL BE PERFORMED BY AN INDEPENDENT TESTING SERVICE AND BE BOUND AND SUBMITTED WITHIN ONE WEEK OF WORK COMPLETION.


INSTALL COAXIAL CABLES AND TERMINATING BETWEEN ANTENNAS AND EQUIPMENT PER MANUFACTURER'S RECOMMENDATIONS, WEATHERPROOF ALL CONNECTIONS BETWEEN THE

ANTENNA AND EQUIPMENT PER MANUFACTURER'S REQUIREMENTS. TERMINATE ALL COAXIAL CABLE THREE (3) FEET IN EXCESS OF ENTRY PORT LOCATION UNLESS OTHERWISE STATED.


G. ANTENNA AND COAXIAL CABLE GROUNDING:

ALL EXTERIOR #6 GREEN GROUND WIRE "DAISY CHAIN" CONNECTIONS ARE TO BE WEATHER SEALED WITH RFS CONNECTORS/SPLICE WEATHERPROOFING KIT #221213 OR FOUAL

ALL COAXIAL CABLE GROUNDING KITS ARE TO BE INSTALLED ON STRAIGHT RUNS OF COAXIAL CABLE (NOT WITHIN BENDS)



ALL DISCREPANCIES FROM WHAT IS SHOWN ON THESE CONSTRUCTION DRAWINGS SHALL BE COMMUNICATED TO ATC ENGINEERING IMMEDIATELY FOR CORRECTION OR RE-DESIGN FAILURE TO COMMUNICATE DIRECTLY WITH ATC ENGINEERING OR ANY CHANGES FROM THE DESIGN CONDUCTED WITHOUT PRIOR APPROVAL FROM ATC ENGINEERING SHALL BE THE SOLE **RESPONSIBILITY OF THE GENERAL CONTRACTOR.** 






- . THIS SITE PLAN REPRESENTS THE BEST PRESENT KNOWLEDGE AVAILABLE TO THE ENGINEER AT THE TIME OF THIS DESIGN. THE CONTRACTOR SHALL VISIT THE SITE PRIOR TO CONSTRUCTION AND VERIFY ALL EXISTING CONDITIONS RELATED TO THE SCOPE OF WORK FOR THIS PROJECT.
- ICE BRIDGE, CABLE LADDER, COAX PORT, AND COAX CABLE ARE SHOWN FOR REFERENCE ONLY. CONTRACTOR SHALL CONFIRM THE EXACT LOCATION OF ALL PROPOSED AND EXISTING EQUIPMENT AND STRUCTURES DEPICTED ON THIS PLAN. BEFORE UTILIZING EXISTING CABLE SUPPORTS, COAX PORTS, INSTALLING NEW PORTS OR ANY OTHER EQUIPMENT, CONTRACTOR SHALL VERIFY ALL ASPECTS OF THE COMPONENTS MEET THE ATC SPECIFICATIONS.
- 3. THIS CONSTRUCTION DRAWING SET IS NOT INTENDED TO REPRESENT ANY ELECTRICAL DESIGN OTHER THAN THE GROUNDING SHOWN, OR TO BE USED TO OBTAIN AN ELECTRICAL PERMIT. AN ELECTRICAL PERMIT IS REQUIRED TO WIRE UP THE PROPOSED EQUIPMENT. ANY ELECTRICAL UPGRADES WILL BE ENGINEERED AND PERMITTED IN A SEPARATE CONSTRUCTION DRAWING SET.


#### LEGEND


8	GROUNDING TEST WELL
ATS	AUTOMATIC TRANSFER SWITCH
В	BOLLARD
CSC	CELL SITE CABINET
D	DISCONNECT
E	ELECTRICAL
F	FIBER
GEN	GENERATOR
G	GENERATOR RECEPTACLE
HH, V	HAND HOLE, VAULT
IB	ICE BRIDGE
К	KENTROX BOX
LC	LIGHTING CONTROL
М	METER
PB	PULL BOX
PP	POWER POLE
Т	TELCO
TRN	TRANSFORMER
 — × ——	CHAINLINK FENCE


#### PROPOSED CABLE NOTES:


- . ESTIMATED LENGTH OF PROPOSED CABLE IS 225'. ESTIMATED LENGTH OF CABLE WAS PROVIDED BY CUSTOMER OR CALCULATED BY ADDING THE RAD CENTER AND THE DISTANCE FROM THE SHELTER ENTRY PLATE TO THE TOWER (ALONG THE ICE BRIDGE) AND A SAFETY FACTOR MEASUREMENT OF 15% (OF THE TWO PREVIOUS VALUES), CDS DEFER TO GREATEST CABLE LENGTH.
- ROUTE PROPOSED CABLES ALONG SAME PATH AS EXISTING CABLES AND IN ACCORDANCE WITH STRUCTURAL ANALYSIS. WHERE POSSIBLE UTILIZE EXISTING CABLE SUPPORT STRUCTURES AS PROVIDED FOR CARRIER TO ADEQUATELY SECURE CABLES, USING EITHER APPROPRIATELY SIZED STAINLESS STEEL SNAP-INS OR MOUNTING HARDWARE AND BRACKETS AS SPECIFIED BY CABLE MANUFACTURER. OTHERWISE, ATTACH CABLES TO HORIZONTAL OR DIAGONAL TOWER MEMBERS USING PROPOSED STAINLESS STEEL ADAPTERS (DO NOT ATTACH TO TOWER LEG).












									AMERICAN TOWER® PLANS PREPARED BY: PLANS PRE
EXISTING ANTENNA SCHEDULE	NOTES			FINAI	ANTENNA SCHE	DULE			CAROLINA PROFESSIONAL LIMITED LIABILITY COMPANY, OR MAH ENGINEERING, LLC, A NEW YORK PROFESSIONAL LIMITED LIABILITY COMPANY, GENERAL CONTRACTOR SERVICES ARE PROVIDED BY TEP OPCO LLC, A DELAWARE LIMITED LIABILITY COMPANY, WE ACQUIRE THE REQUISITE LICRENSES IN EACH
	GC TO VERIFY THE FINAL RFDS	LOCATION			NA SUMMARY		NON ANTENNA SUMM	IARY	REV. DESCRIPTION BY DATE
SECTOR RAD AZ POS ANTENNA BAND MICH STATUS MOUNTED FOURDMENT STATUS CONTRACT STATUS			Z POS	ANTENNA	BAND	MECH D-TILT STATUS	ADDITIONAL TOWER MOUNTED EQUIPMENT	STATUS	A         PRELIMINARY         SDD         11/01/24
A1 P65-15-XI H-RR LIMTS 1900 0° RMV (1) TMA2061F1V1-1 RMV C	TO NOTIFY ATC PM OF ANY DISCREPANCY PRIOR TO	56'-0"	A1	NNH4-65C-R6-V3	OTHER	2° ADD	(1) 4490 B5/B12A	ADD	CONSTRUCTION CAM 11/20/24
ALPHA 56° 60° At ET-X-UW-70-16-70-18- LTE 2001 TE 1000 0° RMV (1) RRH2x40-07L-AT RMV 2. C	NSTALLING THE EQUIPMENT. GC TO CAP ALL UNUSED PORTS.	58'-10"	A2A	AIR6419 B77D	5G CBANI	D - ADD	_		
	CONFIRM SPACING OF PROPOSED ALPH EQUIP DOES NOT CAUSE TOWER CONFLICTS NOR IMPEDE TOWER	PHA 54'-11" 60	A2B	AIR6419 B77G	5G DOD	- ADD		-	$\bigwedge^{\!$
BETA 56' 170° ET-X-UW-70-16-70-18- LTE 700// TE 1900 0° PMV (1) RRH2x40-07L-AT RMV	CLIMBING PEGS.	56'-0"	A3	NNH4-65C-R6-V3	OTHER	2° ADD	(1) 4890 B25/B66 (1) 4478 B14	ADD ADD	ATC SITE NUMBER: 383495
IR-AI-RA (1) B25 KKTI4X3U-4K RMV	S A SCHEMATIC. ATC DID NOT CONFIRM EXISTING SITE	56'-0"	B1	NNH4-65C-R6-V3	OTHER	2° ADD	(1) 4490 B5/B12A	ADD	ATC SITE NAME: MORLEY 1
	CONDITIONS INCLUDING, BUT NOT	58'-10" TA 54'-14" 170	B2A	AIR6419 B77D	5G CBANI		-	-	AT&T MOBILITY SITE NUMBER:
N N	NOUNT CONFIGURATIONS AND	54'-11"	828	AIR6419 B77G	5G DOD		(1) 4890 B25/B66	ADD	COL06029
s	SHOWN ARE FOR REFERENCE	56'-0"	B3	NNH4-65C-R6-V3	OTHER	2° ADD	(1) 4478 B14	ADD	AT&T MOBILITY SITE NAME:
A	ARE APPROXIMATE. THE CONTRACTOR SHALL VERIFY ALL								MOUNT PITTSBURG
E	EXISTING CONDITIONS PRIOR TO NSTALLATION AND NOTIFY ATC								SITE ADDRESS: 15743 PHANTOM CANYON VIEW
	DF ANY DISCREPANCIES. CONTRACTOR TO ENSURE								COLORADO SPRINGS, CO 80903
F	PROPER SEPARATION IN ACCORDANCE WITH AT&T'S								TEP OPCO, LLC
F	IRSTNET REQUIREMENTS.								A
	STATUS ABBREVIATIONS								ANALY
	RMV: TO BE REMOVED								
	RMN: TO REMAIN REL: TO BE RELOCATED								14 58272 F
	ADD: TO BE ADDED								PPT 58272
	CABLE LENGTHS FOR JUMPERS								SSIONAL ENG
	JUNCTION BOX TO RRU: 15' RRU TO ANTENNA: 10'								Commission of the second
									SEAL: 11/20/24
									T&TA 🥰
									AIXI
									DATE DRAWN: 11/20/24
									ATC JOB NO: 14758439 CUSTOMER NAME: MOUNT PITTSBURG
									CUSTOMER ID: COL06029
				BER DISTRIBUTION/SQ		EINIAL	ABLING SUMMARY		
			-	EL NUMBER	STATUS		DC FIBER	STATUS	ANTENNA SCHEDULE
EXISTING FIBER DISTRIBUTION/SQUID EXISTING CABLING SUMMARY				-48-60-18-8F		(2)	0.78" (1) 0.39"		ANTENNA SCIEDULE
MODEL NUMBER STATUS COAX DC/RET FIBER STATUS				-+0-00-10-6F		8 /	7 MM) (10 MM) AWG 6 TRUNK	RMN	ļ
(1) DC6-48-60-18-8F REL (4) 7/8" (2) 0.78" (1) 0.39" (19.7 MM) (10 MM) RMN	EQUIPMENT SCHEDULES	9		_	- (4	, ,	(1) 0.30"	RMN	SHEET NUMBER: REVISION:
8 AWG 6 TRUNK (1)		<u> </u>	(1) DC9-	48-60-24-8C-EV	ADD	- (2) 0.96	" (24.3 MM) (1) 0.39" WG 6 TDLINK	ADD	C-402 0
- $ (4) 1-5/8"$ $  RMV$							TRUNK		

FINAL FIBER DISTRIBUTION/SO	QUID		FINAL CABLING SUMM	ARY	
MODEL NUMBER	STATUS	COAX	DC	FIBER	STATUS
(1) DC6-48-60-18-8F	RMN	(4) 7/8"	(2) 0.78" (19.7 MM) 8 AWG 6	(1) 0.39" (10 MM) TRUNK	RMN
_	—	(4) 1–5/8"	—	_	RMN
(1) DC9-48-60-24-8C-EV	ADD	-	(2) 0.96" (24.3 MM) 6 AWG 6	(1) 0.39" (10 MM) TRUNK	ADD



PROPOSED 2-7/8" MOUNTING PIPE

PROPOSED AIR 6419 B77D ANTENNA

EXISTING SECTOR MOUNT

#### PROPOSED AIR 6419 B77G ANTENNA




					WER PANE DLTS, 1-PH			Ą			
	MAIN	BREA	KER RA		20		and the second	TEM VO	TAGE	(V):	240
DESCRIPTION	VA	c/nc	BKR	POSN	L1	L2	POSN	BKR	c/nc	VA	DESCRIPTION
ERICSSON CAB / OFF	0	с	50/2	1	0		2	60/2	с	0	- TVSS
ERICSSON CAD / OFF	0	с	30/2	3		0	4	00/2	с	0	1035
	0	nc	50/2	5	180		6	20/1	nc	180	GFI REC
850 GSM / OFF	0	nc	50/2	7		1920	8	<mark>20/1</mark>	с	1920	LTS
TELCO REG	1920	с	20/1	9	1920		10	20/1	nc	0	E-911 / OFF
UNKNOWN UMTS GFCI & HEATER	3100	с	20/1 20/1	11		3100	12	20/1	nc	0	E-911 / OFF
ALPHA PDF RECT 1 ALPHA PDF RECT 1	1200	С	20/1 20/1	13	1980		14	20/1 30/1	nc	780	ALPHA GFCI ALPHA PDF RECT 2
UNKNOWN SAID M/W CAB HVAC	3520	с	20/1 20/1	15		4720	16	30/1 30/1	с	1200	ALPHA PDF RECT 2 ALPHA PDF RECT 3
SAID M/W CAB HVAC ALPHA PDF RECT 4	2200	с	20/1 20/1	17	3400		18	30/1 30/1	с	1200	ALPHA PDF RECT 3 ALPHA PDF RECT 5
ALPHA PDF RECT 4	600	с	20/1	19		1200	20	20/1	с	600	ALPHA PDF RECT 5
		PHAS	E TOTAL	S (VA):	7480	10940					·
			SE TOTA		62	91					
CURRENT PER PHA	SE W/ 1259				76		Amperes/	phase ca	annot e	xceed mai	in breaker rating
PANEL TOTA			NEL TOTA		184			Lege	nd: c =	continuou	us, nc = non-continuous





				120/240 VC	DLTS, 1-PH	ASE, 3-W	IRE, 2004	۹.			
	MAIN	BREA	KER RA	FING (A) :	20	0	SYS	TEM VOI	TAGE	(V) :	240
DESCRIPTION	VA	c/nc	BKR	POSN	L1	L2	POSN	BKR	c/nc	VA	DESCRIPTION
RECTIFIER 1.2	1400	с	30/2	1	1400		2	60/2	C	0	- TVSS
RECHIPIEN 1,2	1400	с	30/2	3		1400	4	00/2	с	0	1000
RECTIFIER 3.4	1400	с	30/2	5	1580		6	20/1	nc	180	GFI REC
REC IFIER 3,4	1 <mark>4</mark> 00	с	30/2	7	19	3320	8	20/1	с	1920	LTS
TELCO REG	1920	с	20/1	9	1920		10	20/1	nc	0	E-911 / OFF
UNKNOWN SPARE / OFF	1920	с	20/1 20/1	11		1920	12	20/1	nc	0	E-911 / OFF
SPARE / OFF SPARE / OFF	0	С	20/1 20/1	13	14 <mark>0</mark> 0		14	20/0	С	14 <mark>0</mark> 0	DECTER C
UNKNOWN SAID M/W CAB HVAC	3520	с	20/1 20/1	15		4920	16	30/2	с	1 <mark>40</mark> 0	RECTIFIER 5,6
SAID M/W CAB HVAC SPARE / OFF	1600	С	20/1 20/1	17	3000		18	20/2	С	1400	
SPARE / OFF	0	с	20/1	19		1400	20	30/2	с	1400	RECTIFIER 7,8
		PHAS	E TOTAL	S (VA):	9300	12960					1.cz
			SE TOT		78	108					
CURRENT PER PHA	SE W/ 125%	6 Cont	inuous Lo	ads (A):	97	135	Amperes/	phase ca	annot e	xceed mai	n breaker rating
		PA	NEL TOT,	AL (VA):	222	60		Leger	nd: c =	continuou	is, nc = non-continuous


2 PROPOSED AC PANEL SCALE: N.T.S.





REV.  $\mathbb{A}$  $\land$  $\triangle$ 













#### EQUIPMENT SPECIFICATIONS SCALE: N.T.S.


RAYCA	P SPECIFICA	TIONS		
RAYCAP MODEL	A	В	С	WEIGHT (LBS)
DC9-48-60-24-8C-EV	25.9"	12.4"	9.7"	18.5







( -

ANTENN	IA SPECIFIC	ATIONS		
ANTENNA MODEL	А	В	С	WEIGHT (LBS)
NNH4-65C-R6-V3	96.0"	19.6"	7.8"	102.5
AIR6419 B77D	28.3"	16.1"	7.3"	64.0
AIR6419 B77G	28.3"	16.1"	7.9"	66.1





RRU	SPECIFICA	TIONS		
RRU MODEL	А	В	С	WEIGHT (LBS)
4490 B5/B12A	17.5"	15.1"	6.8"	68.3
4890 B25/B66	17.5"	15.1"	6.9"	68.3
4478 B14	16.5"	13.4"	7.7"	59.9



SUPPLEMENT	AL
SHEET NUMBER: <b>R-601</b>	REVISION:

## NETSURE<sup>™</sup> 5100 SERIES

DC Power System – 2 kW to 28.8 kW

**KEY FEATURES** 

• High Efficiency – 96.2% efficient eSure™ rectifiers ensure optimized total cost

• Solar/Hybrid Capability

(non-integrated version) -

allows for connection of solar

panels and facilitates hybrid

site solutions to reduce grid

• Wide Operating Temperature

Range – rectifiers function at

and OpEx savings on climate

Modular Design – simple to

install and operate; allows

incremental cost effective

• ECO Mode – an innovative

function that enables energy

Remote Access – monitoring

port option available

Battery Management

savings, even at low load operation

through web browsers, TCP/IP &

SNMP as standard, 2nd Ethernet

(582137100 only) – automatic

battery midpoint or block

battery tests in conjunction with

voltage monitoring ensures early

NetSure 5100 System, Integrated

7.2 kW, 19" Rack (582137200)

detection of battery problems

system growth

systems in outdoor applications

without derating, enabling CapEx

-40°C to +80°C, up to +65°C

of ownership

dependency

NetSure™ 5100 Series is designed for wireless access and fixed network applications offering unmatched temperature performance and high power density.

#### Description

The NetSure 5100 Series, a compact -48 volt DC power solution which can provide +24 volt DC power when equipped with converters, features an advanced control unit, a high efficiency rectifier, converter, solar converter and multiple distribution options to meet the demands of many different applications. The system is available in two types; an integrated version and an external distribution version.

The rack mountable 19" wide integrated version (582137200) provides up to 150A at -48 VDC and up to (9) positions available (with expansion rectifier shelf) for 2000 watt high efficiency eSure rectifiers and a distribution panel consisting of either (36) GMT fuse positions, (4) load breakers and (12) GMT fuse positions or (2) load breakers, (2) battery breakers and (12) GMT fuse positions. Optional battery or load low voltage disconnect contactors are available.

The external distribution version (582137100) provides up to 600A at -48 VDC and up to (29) positions available (23" version with five module shelves) for 2000 watt eSure rectifiers. 1500 watt -48V to +24V converters or 2000 watt solar converters, a single or dual row distribution cabinet, and hybrid and solar connectivity panels. The rack mountable 19" or 23" wide power system is available in a number of configurations and designed to work with a wide range of applications. The 23" wide distribution cabinet supports up to (52) 1A to 300A circuit breakers or 1A to 100A TPS/TLS fuses. Options for battery disconnect breaker positions and



NetSure 5100 System, External Distribution 18 kW, 19" Rack (582137100)

dual voltage (-48V /+24V) breaker panels are available. Multiple LVD levels are supported in the dual row distribution configuration, allowing load prioritization in up to two steps.

💙 VERTIV.

Remote monitoring and control is supported by multiple web browsers including IE. Firefox. Chrome and Safari. Standard protocols include ModBus, SNMP V2 & V3. Encrypted security is provided by IPv6 and SNMPV3. Local access is provided through the controllers' keypad and TFT display.

NetSure DC Power systems from Vertiv™ offer extremely low failure rates, as well as low total cost of ownership. The 2000 watt eSure rectifier delivers peak system efficiency above 96%. Maximum value is achieved by an advanced energy optimization function known as ECO mode, enabling energy savings even at low loads.

#### Application

NetSure 5100 Series DC power systems are designed for deployment in telecom access network applications requiring a reliable and high power density supply up to 600 A at -48 VDC or up to 400 A at +24 VDC (external distribution version). The high operating temperature (+65°C) in conjunction with high operational efficiency has a positive impact on climate system dimensioning in outdoor enclosure applications. This DC power system is designed for insertion into EQ zone 4 compliant relay racks and cabinets.



NetSure 5100 System, External Distribution 19.2 kW, 23" Rack (582137100)

NETSURE<sup>™</sup> 5100 SERIES

#### **Technical Specifications**

INPUT	INTEGRATED	SINGLE ROW	TWO ROW
Nominal	Rectifier: 120 VAC, 208 VAC, 240 VAC		208 VAC, 240 VAC 0 VDC to 400 VDC
Operational	Rectifier: (Single Phase) 85 VAC to 300 VAC		e) 85 VAC to 300 VAC 20 VDC to 420 VDC
Frequency	45 Hz to 65 Hz	45 Hz to 65 Hz,	DC (solar input)
Input Connections	Molex	Molex, terminal stri	p or breaker (solar)
ουτρυτ			
Nominal	-48 VDC	-48 VDC /	/ +24 VDC
Adjustable Range	-42 VDC to -58 VDC	-42 VDC to -58 VDC,	+24 VDC to +28 VDC
Capacity (at 40 °C)	1 shelf: 150 A @ 208-240 VAC; 2 shelves: 150 A (N+1) @ 208-240 VAC or @ 120 VAC	400 amps at -48 VDC; 600 amps at -48 VDC with List 27	600 amps at -48 VDC, 400 amps at +24 VDC
Breakers	1A to 150 A E/M or E breakers	1A to 300 A E/	M or E breakers
Fuses	18/100 A to 15 A GMT	3 A to 100 A TPS/TLS a	nd 18/100 A to 15 A GMT
PHYSICAL CHARACT	ERISTICS		
Mounting	Standard 19" rack mounting	Standard 19" and	23" rack mounting
Distribution Shelf / Cabinet Dimensions (H x W x D)	1U x 19" x 15" shelf		8U x (19" or 23") x 15" cabinet lar termination panel)
Module Shelf Dimensions (H x W x D)	1U x 19" x 15"	1U x (19" or 23") x 15"	1U x (19" or 23") x 15"
System Dimensions (H x W x D)	(3.5" up to 5.25") x 19" x 15"	(8.75" to 7.5') x (19" or 23	') x 23.14" (with batteries)
AC Accessibility	Rear/front	Rear	Rear
DC Load Accessibility	Front	Top or rear cabled wit	h front and top access
ENVIRONMENTAL			
Operating	-4	+0°C to +65°C (-40°F to +149°F)	
Storage	-4	40°C to +85°C (-40°F to +185°F)	
STANDARDS COMPL	IANCE		
Safety		UL 1801	
EMC		orms to FCC rules Part 15, Subpa EN55022 Class B, radiated and	
NEBS	Level 3 (pending)	Level 3	Level 3

#### Ordering Information


MODEL NUMBER	PART NUMBER	DESCRIPTION		(0)(+0
NetSure 5100	582137100*	-48V NetSure 5100 DC power system with external distribution		-48 V to +2 C4824-150
NetSure 5100	582137200*	-48V NetSure 5100 DC power system with integrated distribution		04024-100
R48-2000E3	1R482000E3	Rectifier, 2 kW, high efficiency, refer to separate data sheet	6.	Solar Conv
C4824-1500	1C48241500**	Converter, 1.5 kW, high efficiency, refer to separate data sheet		
S48-2000E3	1S482000E3**	Solar converter, 2 kW, high efficiency, refer to separate data sheet	7.	Blank Cove
M830B	1M830BNA*	NCU controller, refer to separate data sheet	8.	Hybrid Pan
* Overall base system or controller number.				

\*\* The converter and solar converter are only used on the NetSure 5100 with external distribution (582137100).

VertivCo.com | Vertiv Headquarters, 1050 Dearborn Drive, Columbus, OH, 43085, USA

© 2018 Vertiv Co. All rights reserved. Vertiv, and the Vertiv logo trademarks or registered trademarks of Vertiv Co. All other names and logos referred to are trade names, trademarks or registered trademarks of their resp taken to ensure accuracy and completeness herein, Vertiv Co. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or ornissions. Specifications are subje

DC-00104 (R11/18)




NOTE: THIS SHEET WAS AT THE REQUES

VERTIV.
Hybrid NetSure <sup>™</sup> 5100 Series, 28.8 kW, 23" Rack with 2 Row Distribution
COVERVIEW
1. Relay Rack
2. Distribution Panel
3. NetSure Control Unit, M830B
4. eSure™ Rectifier, R48-2000e3
548 V to +24 V Converter, C4824-1500
6. Solar Converter, S48-2000e3
7. Blank Cover
8. Hybrid Panel
9. Solar Panel
ared trademarks of their respective owners. While every precaution has been ons. Specifications are subject to change without notice.

CREATED BY OTHERS AND PROVIDED
T OF THE CUSTOMER WITHOUT EDIT.



SHEET NUMBER:




#### Vertiv<sup>™</sup> NetSure<sup>™</sup> DCS48/58-600 Converter System System Application Guide



#### SYSTEM OVERVIEW Description:

-48 VDC to -58 VDC @ up to 600 Amperes Converter System The Vertiv™ NetSure™ DCS48/58-600 Converter System is a complete integrated converter system containing -48 VDC to -58 VDC converters, intelligent control, metering, monitoring, and distribution. The converter system is designed for operation with the positive output grounded.



This system consists of the following components.

DC Distribution Cabinet

The base system includes one (1) distribution cabinet, which provides DC distribution through fuses and/or circuit breakers. The distribution cabinet can be equipped either with a 1-row, 26-position bullet nose type circuit breaker and TPS/TLS fuseholder distribution panel or a distribution panel equipped with four (4) GJ/218 type circuit breaker positions. The distribution cabinet may be equipped with a load disconnect contactor.

A field installed only expansion distribution cabinet is available which provides DC distribution through fuses and/or circuit breakers. The expansion distribution cabinet is equipped with a 1-row, 26-position bullet nose type circuit breaker and TPS/TLS fuseholder distribution panel. The expansion distribution cabinet may be equipped with a load disconnect contactor.

Controller ٠

> NCU (NetSure<sup>™</sup> Control Unit) Controller: The NCU controller provides power system control, converter module control, metering functions, monitoring functions, local/remote alarm functions, and connections for binary inputs and programmable relay outputs. The system also accepts up to two (2) temperature probes to monitor ambient and/or battery temperature. The controller also provides data acquisition and system alarm management. The controller contains a color TFT display and keypad for local access. The controller provides an Ethernet port and comes with comprehensive webpages for local/remote access. The controller has SNMP V3 capability for remote system management. The controller supports software upgrade via its USB port. Refer to the NCU Controller Instructions (UM1M830BNA) for more information.

#### Converter Module Mounting Shelf (Spec. No. 588705300) •

The system contains two (2) Spec. No. 588705300 converter module mounting shelves, each of which houses the converter modules. The top converter module mounting shelf also houses the NCU controller

A field installed only expansion converter module mounting shelf is available. Up to two (2) expansion converter module mounting shelves can be installed in an existing system.

#### -48 VDC to -58 VDC Converter Modules ٠

The system accepts 2000 watt peak, 1600 watt average converter modules to provide -58 VDC load power. Refer to the Converter Instructions (UM1C48582000P3) for more information.

1

Spec. No: 584641000 Model No: DCS48/58-600 Proprietary and Confidential © 2023 Vertiv Group Corp. Page 1

SAG584641000 Revision A. January 27, 2023

Spec. No: 584641000 Model No: DCS48/58-600 Proprietary and Confidential © 2023 Vertiv Group Corp. Page 2

Vertiv<sup>™</sup> NetSure<sup>™</sup> DCS48/58-600 Converter System System Application Guide

#### **General Converter Systems Specifications**

See detailed specifications on page 41.

Family: Spec. No.: Model: DC Input Voltage: DC Output Voltage:

DC Output Capacity: 1C48582000P3 Converter Rating: Agency Approval:

Mounting Type: Mounting Depth: Mounting Height: Access:

Control: Color:

Environment

NetSure™ 584641000 DCS48/58-600 Nominal -48 VDC (-41 VDC to -58.5 VDC). Nominal -57 VDC, positive ground. Output voltage is adjustable from -56.0 VDC to -58.0 VDC via the system controller. 600 A, maximum See UM1C48582000P3. UL Listed to UL/CSA 62368-1 (cULus), Meets NEBS Level 1 Nominal 23" Relay Rack or Equipment Rack Mounting See "Overall Dimensions" on page 43. See "Overall Dimensions" on page 43. Front and Rear for Installation, Expansion, and Maintenance. Front for Operation. Microprocessor Faceplates: Textured Gray Other Surfaces: Bright Zinc -40 °C to +65 °C (-40 °F to +149 °F)

PROPOSED VERTIV CONVERTER SHELF DETAILS

SCALE: N.T.S

SAG584641000 Revision A, January 27, 2023

NOTE: THIS SHEET WAS CREATED BY OTHERS AND PROVIDED AT THE REQUEST OF THE CUSTOMER WITHOUT EDIT.



REVISION -

### **ESURE™ CONVERTER**

C48/24 -1500

# **KEY FEATURES**

#### Converter, 48 to 24 VDC, 1500 W

- High efficiency over 95% reduces power consumption lowering operating costs
- High power density provides more space for revenue generating equipment
- Hot pluggable and interchangeable – for easy expansions and maintenance
- Digital signal processing (DSP) – means fewer components, optimized operation and active load sharing for increased reliability
- Wide input voltage range (41 VDC to 58 VDC) - allows for flexibility, durability and resilience
- Wide operating temperature range from -40°C to +65° - meets the harshest climatic environment requirements
- Compliant with global standards – delivers quality, performance and reliability no matter what the application or location demands

In addition to reducing power consumption and lowering operating cost, eSure™ high-efficiency converters offer superior performance and uncompromised reliability.


VERTIV.

#### Description

The eSure C48/24-1500 high-efficiency converter is designed to operate from a nominal 48 Vdc source to provide nominal 24 VDC load power, which is adjustable to application needs. This constant power converter designed with the latest patented switchmode technology, uses digital signal processing (DSP) for efficient operation.

When redundancy is critical or loads are high, multiple C48/24-1500 converters can be connected in parallel to support a variety of telecom applications. Unified remote management and control of the power system is enabled when combined with a Vertiv<sup>™</sup> controller.





C48 24-1500 Efficiency Curve at 58 VDC Nominal

1

#### **ESURE™ CONVERTER**

#### **Technical Specifications**

DC INPUT	
Voltage	41 VDC to 58.5 VDC
Maximum Current	39.5 A
DC OUTPUT	
Voltage	24 VDC to 28 VDC
Maximum Power	1500 W @ Vout >24 VDC
Maximum Current	63 A @ 48-24 VDC, limit set point 6.3 to 63 A (see figure 1)
Peak Efficiency	>95%
Psophometric Noise (System)	<2 mV; <32 dBrnc
Temperature Derating	See figure 2
CONTROL AND MONITORING	
Rectifier Alarm and Signaling	Alarm and status reported via CAN bus to system controller
Visual Indications	Green LED: Normal Operation Yellow LED: Alarm Red LED: Failure Flashing Red LED: Fan Failure
ENVIRONMENTAL	
Operating	-40°C to +80°C / -40°F to +176°F
Storage	-40°C to +85°C / -40°F to +185°F
Relative Humidity	0 to 95%
Altitude	2000 m / 6560 ft at full power
STANDARDS COMPLIANCE	
Safety	60950 (EN, IEC and UL)
EMC	ETSI EN 300 386 class A, FCC CFR 47 Part 15 class A, Telcordia GR-1089-CORE class A
Environment	REACH, R5, WEEE
MECHANICS	
Dimensions (H x W x D)	41 x 84.5 x 252.5 (mm) / 1.61 x 3.33 x 9.94 (inches)
Weight	1.13 kg / 2.49 lbs

#### **Ordering Information**

MODEL NUMBER	DESCRIPTION
1C48241 500	Converter, 48 to 24 VDC, 1500 W


VertivCo.com | Vertiv Headquarters, 1050 Dearborn Drive, Columbus, OH, 43085, USA

© 2018 Vertiv Co. All rights reserved. Vertiv and the Vertiv logo are trademarks or registered trademarks of Vertiv Co. All other names and logos referred to are trade names, trademarks or registered trademarks of their respective owners. While every precaution has beer taken to ensure accuracy and completeness herein, Vertiv Co. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications are subject to change without notice.

2018.02

#### PROPOSED -48VDC/+24VDC CONVERTER DETAIL SCALE : N.T.S.

1



NOTE: THIS SHEET WAS CREATED BY OTHERS AND PROVIDED AT THE REQUEST OF THE CUSTOMER WITHOUT EDIT.

2



SHEET NUMBER:

REVISION: -

## SUPPLEMENTAL



Figure 2: Output Power vs. Temperature



Output voltage vs. Output current

at max. output power 1500 W

**Figures** 

VERTIV.

Figure 1:

# Vertiv<sup>™</sup> eSure<sup>™</sup> Converter

C48/58 -2000P3

# 

### **Key Benefits**

#### Converter, 48 to 58 VDC, 2000 W Peak / 1600 W Average

- Reduce power consumption and lower operating costs with 95% peak efficiency.
- Easily add capacity with hot pluggable interchangeable components.
- Ensure high availability with wide input voltage range from 41 VDC to 58 VDC.
- Power your 5G sites in the harsh environments with operation from -40°C to +65°C.
- Enjoy peace of mind with high quality UL recognized design.


*Easily support higher power 5G remote radios on cell towers* with modular 2000 watt eSure<sup>TM</sup> power extend converters.

#### Description

The Vertiv™ eSure™ C48/58-2000P3 high-efficiency converter is designed to operate from a nominal -48 VDC source to provide nominal -58 VDC load power, which is adjustable to application needs up to 2000 watts peak, 1600 watts average. This constant power converter designed with the latest patented switchmode technology, uses digital signal processing (DSP) for efficient operation.

The eSure C48/58-2000P3 DC to DC converter is ideal for feeding high power remote radio heads (RRHs). 58 VDC is regulated over a wide input range to minimize voltage drop in the cable feeding the RRH and sustain operation to end of battery discharge. When redundancy is critical or loads are high, multiple eSure C48/58-2000P3 converters can be connected in parallel to support a variety of telecom applications. Unified remote management and control of the power system is enabled when combined with a Vertiv™ NetSure<sup>™</sup> controller.





C48/58-2000P3 Efficiency Curve at 53.5 VDC Nominal Input

1

## Vertiv<sup>™</sup> eSure<sup>™</sup> Converter

#### **Technical Specifications**

**Figures** 

40

D0 lasest	0/0/50 000050
DC Input Voltage	C48/58-2000P3 41 VDC to 58.5 VDC, 48 VDC (nominal)
Maximum Current	53 A
	55 A
DC Output	
Voltage	56 VDC to 58 VDC
Maximum Power	2000 W peak, 1600 W average
	at 40°C, 1280 W average at 65°C
Maximum Current	35.7 A at 2000 W peak (see <i>figure 1</i> ), 28.6 A at 1600 W average, 22.9 A at 1280 W average, all at 56 VDC
Peak Efficiency	>95%
Noise	< 250mV pk-pk; < 20mV rms; <38 dBrnC
Control and Monitoring	
Alarms and Signaling	Alarm and status reported via CAN bus to system controller
Visual Indications	Green LED: Normal Operation Yellow LED: Alarm Red LED: Failure Flashing Red LED: Fan Failure
Environmental	
Operating Temperature	-40°C to +80°C / -40°F to +176°F (see figure 2)
Storage Temperature	-40°C to +85°C / -40°F to +185°F
Relative Humidity	0 to 90%
Altitude	2000 m / 6560 ft at full power
Standards Compliance	
Safety	UL62368-1, EN62368-1, IEC62368-1
EMC	FCC CFR 47 Part 15 Class A conducted and Class B radiated
Environment	REACH, RoHS
Mechanics	
Dimensions (H x W x D)	41 x 84.5 x 252.5 mm / 1.61 x 3.33 x 9.94 inches
Weight	1.13 kg / 2.49 lbs

#### **Ordering Information**


Part Number	Description
1C48582000P3	eSure™ converter, -48 to -58 VDC, 2000 W peak / 1600 W average

#### Vertiv.com | Vertiv Headquarters, 1050 Dearborn Drive, Columbus, OH, 43085, USA

© 2024 Vertiv Group Corp. All rights reserved. Vertiv<sup>®</sup> and the Vertiv logo are trademarks or registered trademarks of Vertiv Group Corp. All other names and logos referred to are trade names, trademarks or registered trademarks of their respective owners. While every precaution has been taken to ensure accuracy and completeness here, Vertiv Group Corp. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications, rebates and other promotional offers are subject to change at Vertiv's sole discretion upon notice.

C48/58-2000P3 (02/2024)

#### PROPOSED -48VDC/-58VDC CONVERTER DETAIL SCALE : N.T.S.



# eSure<sup>™</sup> Rectifier

R48-2000e3

#### **Benefits**

- Optimize the amount of energy delivered and reduce power consumption with over 96% efficiency.
- Increase space for revenue generating equipment with modules that pack more power in a small space with high power density.
- Facilitate easy maintenance, expansion and system changes with hot swappable capabilities.
- Enjoy increased reliability and active load sharing with Digital Signal Processing (DSP) which translates into fewer components and optimized operation.
- Appreciate the flexibility to utilize in a variety of applications with a wide input voltage range of 85 VAC to 300 VAC and full power output at temperatures from -40°C to +65°C.


*In addition to reducing power consumption and lowering* operating cost, eSure<sup>™</sup> high-efficiency rectifiers offer superior performance and uncompromised reliability.

#### Description

The 2000 watt high-efficiency eSure rectifier (model R48-2000e3) converts standard AC supply voltages into stable nominal -48 VDC voltage that is adjustable to application needs. This constant power rectifier designed with the latest patented switch-mode technology, uses DSP (Digital Signal Processing) for efficient operation.

The R48-2000e3 can be connected in parallel with other rectifiers and converters to support a variety of telecom applications. Unified remote management and control of the power system is enabled when combined with a Vertiv<sup>™</sup> controller.





R48-2000e3 Efficiency Curve at 250 VAC Nominal

## eSure<sup>™</sup> Rectifier

VERTIV.

#### **Technical Specifications**

#### **Figures**

AC Input	R48-2000E3	% Watts
Voltage	85 VAC to 300 VAC (see figure 1), 187 VAC to 264 VAC (nominal)	120
Frequency	45 Hz to 65 Hz	100
Maximum Current	12 A	80
Power Factor	>0.99 from 50 to 100% load	60
Protection	High and low voltage protection, surge and lightning protection Adapts to poor quality grid (voltage dip, weak mains) Disconnection at 415 VAC Mains fuses in both lines	40 20 0
DC Output		0
Voltage	-42 VDC to -58 VDC	
Maximum Power	2000 W	
Maximum Current	42 A @ -48 VDC, limit set point 0 to 42 A (see figure 2)	
Peak Efficiency	96.2%	VDC
Protection	Fuse for reverse connection and back feeding protection High voltage shutdown High temperature protection	60
		50
Control and Monitoring		40
Converter Alarm and Signaling	Alarm and status reported via CAN bus to system controller	30
Visual Indications	Green LED: Normal Operation Yellow LED: Alarm Red LED: Failure	20 10 0

Environmental		
Operating	-40°C to 80°C / -40°F to +176°F (see figure 3 for derating)	
Temperature Derating	Full output power up to +65°C at input voltage range 200 to 250 VAC (see figure 3)	
Storage	-40°C to +70°C / -40°F to +158°F	
Relative Humidity	0 to 95%	
Altitude	Full output power up to +65°C at input voltage range @200~ 250 VAC	

Standards Compliance		
Safety	60950-1 (EN, IEC and UL)	
EMC	EN55022, CISPR22, ETSI EN300 286: 2005, FCC CFR 47 Part 15, Telcordia GR-1089-CORE issue 6 (Class B conducted and radiated)	
Environment	REACH, RoHS, WEEE	

#### Mechanics

Dimensions (H x W x D)	41 x 84.5 x 252.5 (mm) / 1.61 x 3.33 x 9.94 (inches)
Weight	1.13 kg / 2.49 lbs

#### **Ordering Information**


Model Number	Description
1R482000E3	eSure™ rectifier, -48 VDC, 2000 W


#### Vertiv.com | Vertiv Headquarters, 1050 Dearborn Drive, Columbus, OH, 43085, USA

© 2020 Vertiv Group Corp. All rights reserved. Vertiv<sup>™</sup> and the Vertiv logo are trademarks or registered trademarks of Vertiv Group Corp. All other names and logos referred to are trade names, trademarks or registered trademarks or registered trademarks of Vertiv Group Corp. All other names and logos referred to are trade names, trademarks or registered trademarks or respistered trademarks of Vertiv Group Corp. All other names and logos referred to are trade names, trademarks or registered trademarks or respistered trademarks of Vertiv Group Corp. All other names and logos referred to are trade names, trademarks or registered trademarks of Vertiv Group Corp. Assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications, rebates and other promotional offers are subject to change at Vertiv's seid discretion upon notice.

R48-2000E3 (R06/20)

**PROPOSED -48VDC RECTIFIER DETAIL** 1 SCALE : N.T.S. % Watts









The PowerSafe® SBS® Front Terminal battery further extends the technical leadership of PowerSafe SBS battery product line: not only do PowerSafe SBS Front Terminal monoblocs retain the benefits typically associated with Thin Plate Pure Lead (TPPL) Technology such as long life, high energy density, superior shelf life, etc., they also deliver exceptional cyclic performance in both float and fast charge applications, even in the hottest and harshest operating environments.

Where conventional Valve Regulated Lead Acid (VRLA)/Absorbed Glass Mat (AGM) batteries struggle to cope with harsh conditions and frequent power outages, cutting edge (TPPL) technology makes PowerSafe 12V batteries the perfect solution for the challenging operating conditions of today's telecommunication networks.

PowerSafe SBS batteries are designed to high quality standards and a unique manufacturing methods means superior energy and power, high performance and proven reliability, there is no substitute to PowerSafe SBS Front Terminal batteries.

#### **Features and Benefits**

- Capacity range 31-190Ah
- 12V monobloc configurations
- Multiple string configurations available
- Two year shelf life
- SR4228 compliant

SYSTEMS

connect@alpinepowersystems.com \$ 877-993-8855

### Installation and Operation

Construction

Robust positive plates are designed to prolong service

• Separators are low resistance microporous (AGM). The

electrolyte is absorbed within the AGM, preventing acid

Container and cover in flame retardant UL94-V0

material, highly resistant to shock and vibration

• Terminals are stainless steel front access with top

access copper alloy insert. Top and front access

terminations provide maximum conductivity · Self-regulating one way pressure relief valves prevents

life and enhance corrosion resistance

spills in case of accidental damage

ingress of atmospheric oxygen


**General Specifications** 

Click to view productiweb page

### Space efficient footprint

- · VRLA design, reduces maintenance requirements Lifting handles for easy handling
- Greater than 10 year life expectancy in float service at 77°F (25°C) • Increased active material surface area yields great
- cycling capability
- Operating temperature: -40°F (-40°C) to 122°F (50°C)
- Recommended temperature: 68°F (20°C) to 86°F (30°C)

	Nominal Ca	pacity (Ah)			Nominal D	imensions		
Cell Type	10 hr rate to 1.80Vpc @20°C	8 hr rate to 1.75Vpc @77°F	Len	ngth mm	Wi	idth mm	He in	ight mm
SBS B8F	31	31	11.9	303	3.8	97	6.3	159
SBS B10F	38	38	11.9	303	3.8	97	7.2	184
SBS B14F	62	62	11.9	303	3.8	97	10.4	264
SBS C11F	92	91	16.4	417	4.1	105	10.1	256
SBS 100F	100	100	15.6	395	4.3	108	11.3	287
SBS 112F	112	112	22.1	561	4.9	125	9.0	228
SBS 145F	145	145	17.9	455	6.8	173	9.4	238
SBS 165F	165	165	17.9	455	6.8	173	10.8	273
SBS 170F	170	170	22.1	561	4.9	125	11.1	283
SBS 190F	190	190	22.1	561	4.9	125	12.4	316









PROPOSED ENERSYS POWERSAFE SBS-190F BATTERY DETAIL SCALE : N.T.S.



Publication No: US-SBSF-RS-004 - January 2014

• Proven long service life • High energy density and cycling capability





Id Operation botprint duces maintenance requirements or easy handling year life expectancy in float service at material surface area yields great / arature: -40°F (-40°C) to 122°F (50°C) temperature: 68°F (20°C) to 86°F (30°C)	Standards • Meets criteria for "non-spillable" batteries • Complies with Telcordia® SR-4228, Network Equipment Building System (NEBS <sup>Tw</sup> ) Criteria Levels • The management systems governing the manufacture of this product are ISO 9001:2008 and ISO 14001:2004 certified	
561       4.9       125         155       6.8       173         155       6.8       173         561       4.9       125         561       4.9       125	Weight - Volumes           in         Imm         Unpacked           6.3         159         22.7         10.3           7.2         184         28.2         12.8           10.4         264         42.0         19.1           10.1         256         61.6         28.0           11.3         287         71.9         32.6           9.0         228         90.4         41.1           9.4         238         105.0         47.7           10.8         273         117.4         53.3           11.1         283         115.7         52.5           12.4         316         132.3         60.0	
SBS 100F-112F	SBS 145F - 190F	
Battery Services fo • Battery Installation • Capacity and Accept • Preventative Mainter backup power te www.alpinepowere	ance hance lecom motive power	
NOTE	E: THIS SHEET WAS CREATED BY OTHERS AND PROVIDED AT THE REQUEST OF THE CUSTOMER WITHOUT EDIT.	SUPPLEMENTAL SHEET NUMBER: REVISION: R-608 -

#### DATA SHEET

DC Surge Protection Solutions for Base Station - Outdoor Rated DC12-48-60-0-25E **Overvoltage Protection and Power Management Junction Box** 

#### **Base Protection - Outdoor**

#### **Strikesorb**<sup>®</sup>

The DC12-48-60-0-25E is designed to be the most robust lightning and power surge protector available for distributed node B or e-node B applications. The flexible design provides electrical protection/cable management at the rooftop or base of sites. The solution employs the patented Strikesorb® 30-V1-HV surge protective device (SPD), capable of providing 60kA (8/20 µs) of surge capacity for up to 12 -48V DC circuits.



#### **Features**

- Provides protection for 12 individual -48V DC circuits at the base of sites
- Surge protection of 60kA 8/20 µs
- Maximum impulse current 5kA 10/350 µs
- Simplifies inter-connectivity and cable management for DC conductors
- UL 1449 4th Edition Type 2 protective device
- IEC 61643-11 Class I protection for DC applications
- Form C relay contacts included, allowing remote monitoring of suppressor status
- Patent pending

#### **Benefits**

[355.60] [509.52] 14.00 20.06

- Strikesorb modules are fully recognized to UL 1449 4th Edition, and IEC 61643-11 Safety Standards, meeting all intermediate and high current fault requirements to facilitate use in original equipment manufacturers (OEM) applications
- Strikesorb offers unique maintenance-free protection against direct lightning currents
- NEMA 4 enclosure allows for indoor or outdoor installation



Strikesorb is a registered trademark of Raycap © 2015 Raycap All rights reserved. G02-00-267 150115

1

Raycap

[569.03] 22.40

www.raycap.com

SPECIFICATIONS DC Surge Protection Solutions for Base Stat DC12-48-60-0-25E **Overvoltage Protection and Power Management Junction** 

#### **Strikesorb**°

El	ectrical		
	Model Number		DC12-48-60-0-25E
	CEQ / ANT Number		CEQ. 12659
	Number of Circuits Protected		12
	Surge Protective Device (SPD) Type per UL 1449 4	Ith Edition	Туре 2
	Surge Protection Class as per IEC 61643-11		Class I
	Nominal Operating DC Voltage [Un]		48 V
	Nominal Discharge Current [In] per UL 1449 3rd Ec	lition	20 kA 8/20 µs
	Maximum Surge Current [Imax] per IEC 61643-11		60 kA 8/20 µs
	Maximum Impulse (Lightning) Current [Iimp] per IEC	61643-11	5kA 10/350 µs
	Maximum Continuous Operating DC Voltage [U <sub>c</sub> ] (M	MCOV)	75 VDC
	Voltage Protection Level [U <sub>p</sub> ] per IEC 61643-11		300 V
	Voltage Protection Rating (VPR)		700 V
	Suppression Technology		MOV
	Strikesorb Module Type 2CA (UL 1449 4th edition)		30-V1-HV
	Protection Modes:	Normal Mode	-48V to Return
		Common Mode	Return to Ground
M	echanical		
	Connection Terminal (Alarm) Method		Form C Hardwired, #22 to #12 AWG [0.34 to 4 mr
	Connection Terminal (Suppression) Method		Compression lug 2 hole, #10, 5/8 pitch, 12-4 AWC
	Connection Terminal (Terminal Block) Method	Copper	#14 to #2 AWG [2.5 to 35 mm <sup>2</sup> ]
		Aluminum	#12 to #2 AWG [4 to 35 mm <sup>2</sup> ]
	Environmental Ingress Protection (IP) Rating		IP 68
	Operating Temperature (°C)		-40° C to +100° C
	Storage Temperature (°C)		-70° C to +80° C

	Operating temperature ( C)		40 0 10 + 100 0
	Storage Temperature (°C)		-70° C to +80° C
	Cold Temperature Cycling IEC 61300-2-22		-30° C to +60° C 200 hrs @5 PSI
	Resistance to Aggressive Materials CEI IEC 61073-2		Including Acids and Bases
	UV Protection ISO 4892-2 Method A		Xenon-Arc 2160 hrs
	Enclosure Type		Outdoor - NEMA 4 Rated
	Enclosure Dimensions $(L \times W \times H)$		18.17"×20.06"×6.37" [461.39×509.52×161.71 m
	Weight		56.3 lbs [25.54 kg]
	Combined Wind Loading	Sustained	135.3 lbs [602 N]
		Gust	228.6 lbs [1016 N]
0	ptional Product Configurations		
	Conduit Fittings		3- 2" Conduit Fittings, 2- 21/2" Conduit Fittings, 1- 1
	Cable Glands (kit included)		3- NPT 1" Cable Glands, 2- M75 Cable Glands, 3-

Strikesorb me	odules are compliant to the following Surge Protection Device Standards:
Standards:	UL 1449 4th Edition: 2011, IEC 61643-11: 2011, EN 61643-11: 2012, IEEE C62.11: 2005, IEEE C62.41: 2

Certifications: UL, VDE, CE





PROPOSED DC12-48-60-0-25E DETAIL

SCALE : N.T.S.


		<
		c
		_
		.C
tion - Outdoor Rated		<
lion - Ouldoor Haled		
n Box		0
mm²] WG [3.31-21 mm²]		
1 mm]		
1- 1" Conduit Fitting		
, 3- M63 Cable Glands		
11: 2002,		
TI. 2002,		
AWG=American Wire Gauge		
us c¶Uus 🚈 CE		
G02-00-267 150115		
	SUPPLEMENTA	
	SHEET NUMBER:	REVISION:
AS CREATED BY OTHERS AND PROVIDED		
EST OF THE CUSTOMER WITHOUT EDIT.	R-609	-
	L	

		PROPRIETARY NOTE: THE DATA AND TECHNIQUES CONTAINED IN THIS DRAWING ARE PROPRIETARY INFORMATION OF VALMON INDUSTRIES AND CONSIDERED A TRADE SECRET. ANY USE OR DISCLOSURE WITHOUT THE CONSENT OF			WING USAGE	СНЕСКЕД ВУ R BMC 5/4/2023	DWG. NO.	CHB-DV		
		DRILLED AND GAS CUT HOLES (± 0.030") - NO CONING OF HOLES LASER CUT EDGES AND HOLES (± 0.010") - NO CONING OF HOLES BENDS AND ANGLES ARE ± 1/2 DEGREE ALL OTHER MACHINING (± 0.030") ALL OTHER ASSEMBLY (± 0.060")		D. DRA CN	AWN BY AFL 5/4/2		A valmont ₹	1-888	-753-7446 Salen Dallas Tamp	n, OR Is, TX
		TOLERANCE NOTES TOLERANCES ON DIMENSIONS, UNLESS OTHERWISE NOTED ARE SAWED, SHEARED AND GAS CUT EDGES (± 0.030")	11				SITE	Supp	ineering Atlant ort Team: Down	<u>tions:</u> York, NY Ita, GA Angeles, CA outh, IN
INISH: IOT DIP GALVANIZED.										
FINISH:	Roome Les connection				ANG	LE LEG CONNECTION	<u> </u>			
	ROUND LEG CONNECTION									
		ORDER SEPARATELY						FLIP FOR ANG		ON
			(							
( j)								63		
A		5x2 6x2		$\sum$				$\sum$		
		3 (4x2)	0					$\sum$		
$\frown$				R				$\sim$		
				$\langle$						
			2" TO 3-1/2 ANGLE I	2" 90° LEGS						
ROUNI	D MEMBERS		6	8 G	58NUT	5/8" HDG HEAVY 2H H	EX NUT		0.13 TOTAL WT. #	1.0 19.
1.9'	'Ø TO 4.5"Ø		5	8 G	S58FW	5/8" HDG USS FLATW/ 5/8" HDG LOCKWAS	HER	1/8 in	0.07 0.03	0.5
				4 X-TC 4 G	OAB-BPL S58R-8	TIE-OFF ANCHOR BRACKET 5/8" x 8" THREADED RO		2 in	0.83 0.70	3.3
				QTY PA 2 V-	ART NO. CLAMP	PART DESCRIPTI		LENGTH 8 21/32 in	UNIT WT. 5.55	NET 11.
				ΟΤΥ ΡΔ			S LIST	LENGTH		NF

PROPOSED SITEPRO HOISTING ANCHOR DETAIL (1)SCALE : N.T.S.

Ψ.
5
$\leq$
Ð
Ψ.
ō
(1)
~
IN I
S
2
D
LL.
=
-
$\leq$
15
C
_
-
۵.
C
1
5
4
Ň
õ
0
$\overline{\mathbf{N}}$
$\odot$
9
E
0
>
0
0
Ó
-


FLIP FOR ANGLE CONNECTION		
Engineering Support Team: 1-888-753-7446 COMPANY Locations: New York, NY Locations: New York, NY Salem, OR Tamias, TX Tampa, FL		
CHB-DVC4 CHB-DVC4	PAGE 1 OF 1	





# Product Info

# HGxx: Lace-Up Hoisting Grips



#### Features:

- Lace-up design allows installation after connectors have been installed
- Longer grips result in less cable stress and greater resistance to pull-out, flexure, and vibration
- Use for lifting cables and for strain relief at 200' intervals on long cable runs

#### Construction:

• Stainless steel braided wire construction


Part #	Cable Size & Type	Overall Length	Mesh Length	Weight
HG12	1/2″ Coax & LMR-600	15″	8″	0.1 lb
HG58	5/8" Coax & LMR-900	29″	22″	0.3 lb
HG78	7/8″ Coax & LMR-1200	34″	21-1/2″	0.4 lb
HG114	1-1/4″ Coax & LMR-1700	40″	27″	0.4 lb
HG158	1-5/8" Coax	45″	30″	0.4 lb
HG214	2-1/4" Coax	45″	30″	0.6 lb

New York	Georgia	Indiana	Oregon	California	Texas	Florida
1-888-438-7761	1-866-901-0603	1-888-753-7446	1-888-880-9191	1-888-776-1937	1-888-809-5151	1-844-278-6371

#### PROPOSED SITEPRO HOISTING GRIP DETAIL 1

SCALE : N.T.S.





SXK 125 5394/2

# Universal B2B Bracket CC110

Universal B2B Bracket CC110 is designed for installation of back to back ERS on any supporting structure i.e. pole, mast, tower leg etc. It is Low PIM bracket. When installed properly, it meets the requirements of installation in High Risk PIM Zones. Static and dynamic testing was conducted as per IEC 61000-4-3: 2020 PRV and ITU-R SM-329.


#### Robustness

The Universal B2B Bracket CC110 kit supports for installation of back to back ERS weight upto 50 kg on each side simultaneously. It supports the ERS mounting on pole, mast, tower leg or square tube. Easy installation due to use of carriage bolts for mounting on the supporting structure and key holes for ERS in the bracket. Bush separators has been provided to avoid any contact of arms with each other.

#### Quality

All components of the assembly are made of galvanized High Tensile Steel, which supports corrosion resistance.






#### Ericsson | SXK 125 5394/2

# **Technical specification**

### **Functional Description**

#### SXK 125 5394/2

Universal B2B Bracket CC110 kit supports installation of ERS back to back with Centre to 30mm x 110mm, 80mm x 110mm and 110mm x 110mm. It also supports two RRUs (bac Centre to Centre distance of 146mm x 264.5 mm (old generation ERS). ERS or RRU are m back in portrait position on any supporting structure with ERS or RRU weight up to 50kg of the second structure w



Product	Universal B2B Bracket CC110					
Product number	SXK 125 5394/	2				
Mounting range	Profile	Minimum	Maximum			
	Circular tube	Ø25 mm (1 inch)	Ø120 mm (4.7 inch)			
	60º Angle	35 mm Open (1.4 inch)	· ,			
	90º Angle	35 x 35 mm	112 x 112			
	Square tube	(1.4 X 1.4 inc 35 x 35 mm (1.4 X 1.4 inc	80 x 80 mr			
Mechanical specification						
	Brackets	High Tensile	Steel, Galvanized			
	Fasteners	Grade 8.8 G	alvanized & A4			
	Bush Separator	s Composite r	naterial(PBT+PE1			
Recommended tools						
	M8 ISO, 13mm	torque wrench (	10-22 Nm)			
	M10 ISO, 16mr	n & 17mm torqu	e wrench (15-25			
Performance						
	Maximum wind	l speed	67 m/s (240 k			
	Survival wind s	Survival wind speed 90 m/s (				
	Maximum equi	oment weight	2 x 50 Kg (2 x			
Packaging dimension	Length Wid	th Height	Package Weig			
Universal B2B Bracket CC110 (SXK 125 5394/2)		mm 80 mm 2 in) (3.2 in)	10.4 Kg (22.9 lbs)			

ericsson.com

287 01- SXk

# 1 PROPOSED RRU BACK TO BACK BRACKET DETAIL

SCALE: N.T.S.

May 2021 2	
e to Centre distance of back to back) with e mounted back to kg on each side.	
um	
nm ch)	
m Opening ch)	
112 mm	
4.4 inch) 3 mm	
3.1 inch)	
nized A4	
PET)-GF30	
-25 Nm)	
40 km/h, 149 mph) 24 Km/h, 201 mph)	
(2 x 110.2 lbs)	
/eight Product Weight 10.0 Kg (22.0 lbs)	
XK 125 5394/2, Rev. A ©Ericsson AB 2021	
	SUP
	SHEET
WAS CREATED BY OTHERS AND PROVIDED QUEST OF THE CUSTOMER WITHOUT EDIT.	R-6

# SUPPLEMENTAL



REVISION:

# Pxxx: Bulk Pipe

SITE PRO A valmont 🌾 company

Part #	Length	OD x Length (in)
	Schedu	ıle 40
P260	5'-0"	2-3/8" x 60"
P263	5'-3"	2-3/8" x 63"
P272	6'-0"	2-3/8" x 72"
P284	7'-0"	2-3/8" x 84"
P296	8'-0"	2-3/8" x 96"
P2108	9'-0"	2-3/8" x 108"
P2120	10'-0"	2-3/8" x 120"
P2126	10'-6"	2-3/8" x 126"
P2150	12'-6"	2-3/8" x 150"
P2174	14'-6"	2-3/8" x 174"
P2252	21'-0"	2-3/8" x 252"
P3072	6'-0"	2-7/8" x 72"
P3084	7'-0"	2-7/8" x 84"
P3096	8'-0"	2-7/8" x 96"
P30108	9'-0"	2-7/8" x 108"
P30120	10'-0"	2-7/8" x 120"
P30126	10'-6"	2-7/8" x 126"
P30150	12'-6"	2-7/8" x 150"
P30174	14'-6"	2-7/8" x 174"
P30252	21'-0"	2-7/8" x 252"
P360	5'-0"	3-1/2" x 60"
P372	6'-0"	3-1/2" x 72"
P384	7'-0"	3-1/2" x 84"
P396	8'-0"	3-1/2" x 96"
P3150	12'-6"	3-1/2" x 150"
P3160	13'-4"	3-1/2" x 160"
P3174	14'-6"	3-1/2" x 174"
P3216	18'-0"	3-1/2" x 216"
P3252	21'-0"	3-1/2" x 252"
P472	6'-0"	4-1/2" x 72"
P4126	10'-6"	4-1/2" x 126"
P4252	21'-0"	4-1/2" x 252"



#### Features:

Factory cut end, hot-dip galvanized pipe

#### Construction:

• ASTM A53 Grade B Schedule 40 or Schedule 80

#### Design Criteria:

ASTM A53 Grade B (Yield Fy = 35 ksi [240 MPa]/ Tensile Fu = 60 ksi [415 MPa])

• Hot dip galvanized in accordance with ASTM A123 requirements

Part #	Length	OD x Length (in)
Schedule 80		
P2252-80	21'	2-1/2" x 252"
P30126-80	10'-6"	2-7/8" x 126"
P30252-80	21'	2-7/8" x 252"
P3252-80	21'	3-1/2" x 252"

888-438-7761

#### SitePro1.com



# Pxxx: Bulk Pipe

Part #	Length	OD x Length (in)
	Sched	ule 40
P260	5'-0"	2-3/8" x 60"
P263	5'-3"	2-3/8" x 63"
P272	6'-0"	2-3/8" x 72"
P284	7'-0"	2-3/8" x 84"
P296	8'-0"	2-3/8" x 96"
P2108	9'-0"	2-3/8" x 108"
P2120	10'-0"	2-3/8" x 120"
P2126	10'-6"	2-3/8" x 126"
P2150	12'-6"	2-3/8" x 150"
P2174	14'-6"	2-3/8" x 174"
P2252	21'-0"	2-3/8" x 252"
P3072	6'-0"	2-7/8" x 72"
P3084	7'-0"	2-7/8" x 84"
P3096	8'-0"	2-7/8" x 96"
P30108	9'-0"	2-7/8" x 108"
P30120	10'-0"	2-7/8" x 120"
P30126	10'-6"	2-7/8" x 126"
P30150	12'-6"	2-7/8" x 150"
P30174	14'-6"	2-7/8" x 174"
P30252	21'-0"	2-7/8" x 252"
P360	5'-0"	3-1/2" x 60"
P372	6'-0"	3-1/2" x 72"
P384	7'-0"	3-1/2" x 84"
P396	8'-0"	3-1/2" x 96"
P3150	12'-6"	3-1/2" x 150"
P3160	13'-4"	3-1/2" x 160"
P3174	14'-6"	3-1/2" x 174"
P3216	18'-0"	3-1/2" x 216"
P3252	21'-0"	3-1/2" x 252"
P472	6'-0"	4-1/2" x 72"
P4126	10'-6"	4-1/2" x 126"
P4252	21'-0"	4-1/2" x 252"



#### Features:

• Factory cut end, hot-dip galvanized pipe

#### Construction:

ASTM A53 Grade BSchedule 40 or Schedule 80

#### Design Criteria:

ASTM A53 Grade B (Yield Fy = 35 ksi [240 MPa]/ Tensile Fu = 60 ksi [415 MPa])

- Hot dip galvanized in accordance with ASTM A123 requirements

Part #	Length	OD x Length (in)
	Schedule 8	D
P2252-80	21'	2-1/2" x 252"
P30126-80	10'-6"	2-7/8" x 126"
P30252-80	21'	2-7/8" x 252"
P3252-80	21'	3-1/2" x 252"

#### SitePro1.com

#### PROPOSED 8' PIPE MOUNT DETAIL 2

SCALE: N.T.S.

S CREATED BY OTHERS AND PROVIDED	
ST OF THE CUSTOMER WITHOUT EDIT.	

#### 888-438-7761





SHEET NUMBER:

**REVISION:** -

# XP-197-US



Single Crossover Plate kit for MT-197 Stand-off: Mounts one 2-3/8"-3-1 /2" Pipe to 4-1/2" Round or 4" Square Members

#### Product Classification Product Type Pipe mount kit General Specifications Mounting Stand-off arm 0 Pipe, quantity Dimensions 10 in | 254 mm Height Width 10 in | 254 mm 10 in | 254 mm Length 4.5 in | 114.3 mm Mounting Diameter, maximum Pipe Outer Diameter 2.4 in | 60.96 mm | 2.9 in | 73.66 mm | 3.5 in | 88.9 mm

Hot dip galvanized steel

### Material Specifications

Material Type

### Packaging and Weights

Included	Crossover bracket   Hardware
Packaging quantity	1
Weight, net	11.3 kg   24.912 lb

### Regulatory Compliance/Certifications

Agency	Classification	
CHINA-ROHS	Below maximum concentration value	

# Page 1 of 2 ©2023 CommScope, Inc. All rights reserved. All trademarks identified by ® or <sup>™</sup> are registered trademarks, respectively, of CommScope. All specifications are subject to change without notice. See www.commscope.com for the most current information. Revised: March 23, 2023 ©2023 CommScope, Inc. All rights reserved. All trademarks identified by © or are registered trademarks, respectively, of CommScope. All specifications are subject to change without notice. See www.commscope.com for the most current information. Revised: March 23, 2023 COMMSCOPE® PROPOSED CROSSOVER PLATE KIT DETAIL

1

# XP-197-US

SCALE: N.T.S.

REACH-SVHC ROHS

Compliant as per SVHC revision on www.commscope.com/ProductCompliance Compliant Compliant





SHEET NUMBER: R-614 REVISION: -

# **SUPPLEMENTAL**

Page 2 of 2



CORPORATION

This report was prepared for American Tower Corporation by



### Antenna Mount Analysis Report

Mount Type	: 10.5-ft Sector Frame
ATC Site Name	: Morley 1, CO
ATC Site Number	: 383495
Engineering Number	: 14758439_C8_01
<b>Mount Elevation</b>	: 55 ft
Carrier	: AT&T Mobility
Carrier Site Name	: MOUNT PITTSBURG
Carrier Site Number	: WSUTH0032710
Site Location	: 15743 Phantom Canyon View
	Colorado Springs, CO 80903
	38.6126, -104.9348
County	: El Paso
Date	: October 28, 2024
Max Usage	: 50%
Result	: Contingent Pass

Prepared By: Dmitriy Albul Professional Enginee

SMJ International, LLC - 49030 Pontiac Trail, Suite 100 - Wixom, MI 48393 - 616.745.4777 Office - info@smj-llc.com

Reviewed By:



SMJ International Eng. Number 14758439\_C8\_01 October 28. 2024 Page 4

#### Conclusion


Based on the analysis results, the antenna mount meets the requirements per the applicable codes listed above provided the modifications listed below are completed:

- Move the existing beta sector mount to the tower leg with the existing Pike omni antenna to become alpha sector and rotate the existing alpha sector mount to azimuth to become new beta sector.
- Install two (2) Site Pro 1 P30120 mount pipes in position 2. Connect pipes to the sector frame rails with Commscope XP-197-US crossover plate kits (or approved equivalent).
- Install four (4) Site Pro 1 P296 RRH pipes. Connect pipes to the sector frame arms with Commscope XP-197-US crossover plate kits (or approved equivalent).

No structural failures were addressed with the noted contingencies. Contingencies address the Carrier's antenna spacing requirements.

If you have any questions or require additional information, please reach out to your American Tower contact. If you do not have an American Tower contact and have an Engineering question, please contact MountAnalysis@americantower.com. Please include the American Tower site name, site number, and engineering number in the subject line for any questions.

SMJ International, LLC - 49030 Pontiac Trail, Suite 100 - Wixom, MI 48393 - 616.745.4777 Office - info@smj-llc.com



10-28-24 Expiration Date: 10-31-25

> NOTE: THIS SHEET WAS CREATED BY OTHERS AND PROVIDED AT THE REQUEST OF THE CUSTOMER WITHOUT EDIT. PLEASE REFERENCE THE MOUNT ANALYSIS REPORT FOR COMPLETE MOUNT ANALYSIS CALCULATIONS AND DETAILS. SUPPLEMENTAL PAGES INCLUDED IN THE CONSTRUCTION DRAWINGS ARE FOR REFERENCE ONLY, GENERAL CONTRACTOR IS TO VERIFY THEY HAVE THE MOST RECENT MOUNT ANALYSIS PRIOR TO CONSTRUCTION.

SHEET NUMBER:	
R-615	

REVISION: -